

Manuals and documents in further languages:
https://eltako.com/redirect/PL-SAM1LT

PC software SIENNA-Professional page 4-9.

Typical connections on page 4-10.

PL-SAM1LT

MIN

Powerline TLZ (staircase time switch) actuator with 1 channel. 53 x 43 mm, 25 mm deep for mounting in 58 mm switch boxes. Off delay settable from 1 minute to 120 minutes. Switch-off early warning settable. 1 NO contact not potential free 10 A/250 V AC, incandescent lamps 2000 watts. Sensor input 230 V. Standby loss only 0,5 watt. To control and switch at the same place.

Two rotary switches are located on the front for address assignment:
The left rotary switch defines the group address g with 16 alphabetical values from A to P.
The right rotary switch determines the off-delay time.
Above it is a slide switch which acts **as a configuration switch with positions 0, 1 and 2.**
Position 0: Pushbutton at sensor input with subsequent switching.
Position 1: Same as Position 0 but with switch-off early warning.
Position 2: A change-over switch is evaluated as a pushbutton.
All entries and configurations can also be accessed via the mains using the PC software SIENNA Professional (see page 4-9).
To the left of the rotary switches is a red LED which indicates all activities.
Next to it is a reset pushbutton and to the right of that is a service pin. For functions, please refer to the operating instructions.
The terminals located above are plug-in terminals for conductor cross-sections of 0.2 mm^2 to 1.5 mm^2.

PL-SAM1LT	Powerline TLZ actuator 1 channel with sensor input 230 V	**Art. No. 31100004**	**115,30 €/pc.**