





Trennbrücke TB14

**Manuals and documents in further languages:**
https://eltako.com/redirect/FSNT14-12V*12W

*Housing for operating instructions GBA14 page 1-49.*

# FSNT14-12V/12W

**Switching power supply unit rated capacity 12 W. Standby loss 0.1 watt only.**

Modular devices for DIN 60715 TH35 rail mounting. 1 module = 18 mm wide, 58 mm deep.
**If the total power demand of a Series 14 bus system is higher than 8 W, other switching power supply units FSNT14-12V/12W are required. These are each supplying a group of actuators, which are separated with a disconnecting link on the FSNT14.**
The scope of delivery includes 1 disconnecting link TB14 1 module, 1 jumper 1.5 modules and a spacer DS14.
At a load of more than 50% of the rated capacity and always if there are adjacent switching power supply units and dimmers a ventilation clearance of 1/2 module must be maintained with the spacers DS14.
Therefore, this and a long jumper are included to the dimmers.
Input voltage 230 V (-10% to +10%). Efficiency 87%.
Stabilised output voltage ±1%, low residual ripple. Short-circuit proof.
Overload protection and over-temperature switch-off by means of swichting off with automatic switching-on after fault clearance (autorecovery function).
This switching power supply unit can also be used for producing a redundancy. Therefore only 1 FSNT14 should be plugged in parallel to the integrated power supply units into the FAM14 and FTS14KS and connected to a normal jumper. For an optimal load distribution, the FSNT14 should be placed as close as possible next to the last bus actuator.

| | | | |
|---|---|---|---|
| **FSNT14-12V/12W** | Switching power supply unit 12V/12W | **Art. No. 30014062** | **42,40 €/pc.** |

Recommended retail prices excluding VAT.